

# **Product Information**

#### **Application and Performance Specifications**

#### **Description:**

• Line Voltage: 120 vac, + 5%, - 10%, 60Hz

Preheat Start

•	Low	Power	Facto
---	-----	-------	-------

Typical Performance Data											
Lamp			Input Current	Input Power	Power	Ballast	Ballast Efficacy	T.H.D.	Crest		
Туре		#	(Amps)	(Watts)	Factor	Factor	Factor	%	Factor		
F25T12		1	0.42	29	< .60	.90	3.10	< 10	< 1.7		

Application and Performance Specification Information Subject to Change without Notification.

#### Performance:

- Designed in accordance with ANSI C82.1
- · Compatible with PLC and IR systems
- · Reactor type circuit

#### **Application:**

- Minimum Starting Temperature: 50° F, 10° C
- Maximum Ballast Case Temperature not to exceed 90° C
- · Sound Rated: A
- Remote Mounting: 20 feet with minimum 18 AWG ( refer to TechNote # 7b for other wire sizes/lengths )

#### Safety:

• No PCB's

• Weight:

- UL listed (Class P, Indoor and Type 1 Outdoor, HL)
- CSA Certified


#### Mechanical: Overall Mounting • Length: 3 1/16" 2 3/4" • Width: 1 25/32" · Height: 1.5" • Lead Length (inches, ± 1):

Black 12 Black 22 .70 lb.

### Warranty:

The manufacturer warrants to the purchaser that each electronic ballast will be free from defects in material or workmanship for a period of 24 months from date of manufacture when properly installed and under normal conditions of use.

## Manufactured in North America



Ballast must be grounded. Install in accordance with National Electric Code.